

BLODGETT HV100G - Parameters for Motor Inverter Drive

NOTE: Oven connected to power, mode switch in "OFF" position. Display should read " 0.0"

PRESS		DISPLAY
FUNC		d 0 1
▼	keep pushing until	A - -
FUNC	twice	A 0 1
▲	once	0 2
STR	to save	A 0 1
▲	keep pushing until	A 2 0
FUNC	once	
▲	push + hold until	2 0. 0
STR		A 2 0
▲	once	A 2 1
FUNC	once	
▲	push + hold until	3 0. 0
STR	to save	A 2 1
▲	once	A 2 2
FUNC	once	
▲	push + hold until	4 0. 0
STR	to save	A 2 2
▲	once	A 2 3
FUNC	once	
▲	push + hold until	5 0. 0
STR	to save	A 2 3
▲	keep pushing until	A 5 1
FUNC	once	
▲	once	1
STR	to save	A 5 1
▲	once	A 5 2
FUNC	once	
▲	keep pushing until	1 0
STR	to save	A 5 2
▲	keep pushing until	A 5 5
FUNC	once	
▲	push + hold until	2. 0
STR	to save	A 5 5
▲	push + hold until	b 0 1
FUNC	once	
▲	keep pushing until	2
STR	to save	b 0 1
▲	once	b 0 2
FUNC	once	
▲	push + hold until	2 5. 0
STR	to save	b 0 2
▲	keep pushing until	b 2 2
FUNC	once	
▼	keep pushing until	3. 6 0
STR	to save	b 2 2
▲	keep pushing until	b 8 3
FUNC	once	
▲	keep pushing until	1 2. 0
STR	to save	b 8 3

PRESS		DISPLAY
▲	keep pushing until	C 0 3
FUNC	once	
▼	keep pushing until	2
STR	to save	C 0 3
▲	once	C 0 4
FUNC	once	
▼	push + hold until	3
STR	to save	C 0 4
▲	once	C 0 5
FUNC	once	
▲	keep pushing until	1 2. 0
STR	to save	C 0 5
▲	keep pushing until	C 1 4
FUNC	once	
▼	once	0
STR	to save	C 1 4
▲	once	C 1 5
FUNC	once	
▲	once	1
STR	to save	C 1 5
▲	keep pushing until	C 2 2
FUNC	once	
▲	keep pushing until	5
STR	to save	C 2 2
▲	keep pushing until	C 7 1
FUNC	once	
▲	once	0 0
STR	to save	C 1 4
▲	to save	C 1 5
FUNC	once	
▲	once	1
STR	to save	C 1 5
▲	keep pushing until	C 2 2
FUNC	once	
▲	keep pushing until	5
STR	to save	C 2 2
▲	keep pushing until	C 7 1
FUNC	once	
▼	keep pushing until	6
STR	to save	C 7 1
▲	keep pushing until	F 0 2
FUNC	once	
▼	keep pushing until	1. 5
STR	to save	F 0 2
▲	once	F 0 3
FUNC	once	
▼	keep pushing until	2. 5
STR	to save	F 0 3
▼	keep pushing until	d 0 1